



产品名称:歌尚蓝牙耳机  
 主要功能:蓝牙(通话)+AUX  
 AUX功能:不开机插上即可使用;开机后插入AUX线自动关闭蓝牙功能  
 开机状态:5分钟无设备连接自动关机

**产品参数**

有效范围: 8-10m  
 充电时间: ≈2h  
 续航时间: ≈10h  
 灵敏度: 102±3 dB/mW  
 阻抗: 32ohm  
 喇叭直径: 40mm

**包装清单**

- 一个蓝牙耳机主机
- 一根 USB 充电数据线
- 一根 AUX -in 音频线
- 一本使用说明书



**按键说明**

1. “ ” 开启/关闭
2. “ ” 短按减音量/ 长按上一曲
3. “ ” 短按加音量/ 长按下一曲
4. “ ” 暂停/播放

**功能说明**

开机: 长按 “ ” 三秒钟以上, 设备启动自动进入蓝牙模式, LED 指示灯蓝色长亮。  
 关机: 长按 “ ” 三秒钟以上, LED 指示灯熄灭, 设备关闭。

**按键指引**

- 1.接通电话:来电时短按 “ ”
- 2.挂断电话:通话中短按 “ ”
- 3.回拨最后一次电号码:双击 “ ”
- 4.播放音乐:正常状态下短按 “ ”,自动打开智能设备播放音乐。
- 5.通话后继续播放:有来电时,自动暂定播放中的音乐,通话结束后,需要短按 “ ”继续播放。

**蓝牙模式**

- 1.开机自动进入蓝牙模式,语音提示:“ Power on, pairing ”, LED指示灯蓝色长亮,3秒后如若搜索不到最后一次与之连接的蓝牙设备,耳机自动进入蓝牙配对模式,LED指示灯蓝红快速交替闪烁,打开智能设备的蓝牙功能,开启搜索并选择设备“ E92”,无需密码,配对成功后语音提示“Connected”,LED指示灯蓝色长亮,工作状态为两秒闪烁一次。

- 2.重新配对:关闭已连接智能设备的蓝牙功能,此时,蓝牙耳机与上次配对设备断开连接,LED指示灯蓝红闪烁进入配对模式,打开新的智能设备的蓝牙功能,开启搜索并选择设备“ E92 ”,无需密码,配对成功后语音提示“Connected”,LED指示灯蓝色长亮,工作状态为两秒闪烁一次。
- 3.后续配对:开机后3秒内,会自动搜索并连接最后一次与之配对的设备。
- 4.最大音量警示音:“didi”。
- 5.省电模式:匹配状态持续5分钟无任何操作,耳机自动关机;插入AUX-in线自动切断供电。

**AUX-in 播放模式**

在任意模式下,插入AUX-in线,耳机自动关机,切换到AUX-in功能,此时无需耗电。

**LED灯状态**

充电状态	红色LED指示灯长亮,满电时,蓝灯长亮
开机状态	蓝色LED指示灯长亮
关机提示	LED指示灯熄灭

配对状态	红蓝LED指示灯交替闪烁
连接成功	蓝色LED指示灯慢闪
使用状态	Bluetooth Mode,蓝色LED指示灯闪烁 AUX-in Mode,耳机自动关机,LED指示灯熄灭

**注意事项**


- 蓝牙耳机进入配对模式后若无配对连接操作,请关闭设备避免电量损耗。
- 搜索蓝牙耳机时,不要进行其他操作,以免程序出错。
- 在使用中请选择适当音量,以防对耳朵造成伤害。
- 请注意蓝牙耳机的良好使用环境,以防对耳机造成伤害。
- 长时间未使用耳机,请先将耳机充满电后再使用。

**Product Name:** Gorsun-Bluetooth headphone  
**Function:** Bluetooth (call) and AUX  
**AUX function:** It can be used without powering on,and will automatically power-off after using AUX cable.  
**Power on status:** auto power-off after disconnected for 5 minutes.

**Specifications**  
 Working Range: up to 8-10m  
 Charging Time: about 2H  
 Working Time: about 10H  
 Sensitivity: 102±3 dB/mW  
 Impedance: 32ohm  
 Speaker diameter: 40mm

**Packing list**

- A bluetooth headphone
- An USB charging cable
- An AUX -in audio cable
- A manual



**Button Function**

1. “ ” Power on/Power off
2. “ ” Volume down: short press Move next: long press
3. “ ” Volume up: short press Move previous: long press
4. “ ” Pause / play

**Function Description**

- 1.Power on: Long press “ ” for more than 3 seconds,the headphone turn on and enter Bluetooth Mode,Blue LED is on.

- 2.Power off: Long press “ ” for more than 3 seconds,the LED indicator light is off and the headphone turn off.

**Button Guide**

- 1.Hang on:Short press “ ” button when calling.
- 2.Hang up:Short press “ ” button when being called.
- 3.Dial back : Double click “ ” button.
- 4.Play music: Normally short press “ ” button to turn on the smart devices automatically to play music.
- 5.Continue to play music after the call:When there is an incoming call, the music will be automatically suspended. After the call, you need to short press the “ ” button to continue playing.

**Bluetooth mode**

- 1.First pairing: It will enter the Bluetooth mode automatically

when the “ E92 ” is switched on,then voice prompts, "Power on, pairing", blue LED is on, and if the last connected device could not be found after 3s, the “ E92 ” will automatically enter the Bluetooth pairing mode, and you will find that LED light flashed between red and blue,at this time,turn on the Bluetooth function of the smart devices, then search the device named " E92 " to get connected without a password, after pairing successfully, voice prompts "Connect-ed", the blue LED is on and flash per 2 seconds after working.

- 2.Repairing: turn off the Bluetooth function of the connected smart devices, at this time,the Bluetooth headset and the last matching device got disconnected,LED light flashed between red and blue,and enter the Bluetooth pairing mode,then turn on the Bluetooth function of the smart devices, search the device named "E92" to get connected without a password, after pairing successfully, voice prompts "Connected", the blue LED is on and flash per 2

- seconds after working.
- 3.Subsequent pairing: 3 seconds after powering on, it will automatically search and connect the smart device which paired last time.
- 4.Warning voice of maximum volume : "Didi"
- 5.Power saving mode:headset will automatically power off after pairing continuously for 5 minutes;it will cut off power supply automatically after using Aux-in cable for power saving.

**AUX - in Mode**

In any modes, insert the AUX-in line, the headset automatically shut down, and switch to AUX-in function

without power consumption.

**LED Instructions**

Charging	The red LED is on, when full charged, the indicator light is off
Powering on	Blue LED flashes
Powering off	Red LED flashes and finally turn to off
Pairing	Blue and red LED flashes alternately

Standby	Blue LED is on
Connected	Blue LED is on
Working	Bluetooth Mode, blue LED is on AUX-in Mode, headphone turn off automatically, LED indicator lights off



**Note**

1. Please turn off the device to avoid power consumption if no pairing operation taken after bluetooth headset entering into the pairing mode.
2. Please do not make other operations when searching bluetooth in case of procedure error.
3. Please adjust volume appropriately to avoid doing harm to the ears.
4. Please pay attention to choose a good surroundings for bluetooth headset use to avoid causing damage to the headset.
5. Please get bluetooth headset full charged firstly when it has not being used for a long time.